

Medium & Large Mammal Transmitters

WMI

Transmitter Number	Type	Battery	Dimensions LxWxH (cm)	Mounted Weight* (grams)	Pulse Width (ms)	Pulse Rate (ppm)	Peak Current (ma)	Antenna Length 218 MHz (cm)	Power Output (dBm)	Battery Life (days)	Typical Species
HLPM-32200	3 Stage	3.5 v 38.0 ah Li	11.5x7.5x4.5	450-460	35	70	18	38 whip	+10 to +13	1800	elephant, elk, bear
HLPM-32200A	3 Stage	3.5 v 38.0 ah Li	11.5x7.5x4.5	450-460	35	60-120	18	38 whip	+10 to +13	1400	elephant, elk, bear
HLPM-31100	3 Stage	3.5 v 19.0 ah Li	10x4.1x4.5	350-360	35	70	18	30.5 whip	+10 to +13	900	deer, lion, feral hog
HLPM-31100A	3 Stage	3.5 v 19.0 ah Li	10x4.1x4.5	350-360	35	60-120	18	30.5 whip	+10 to +13	703	deer, lion, feral hog
HLPM-3140	3 Stage	3.5 v 8.5 ah Li	8.5x3.3x3.7	160-170	25	55	15	28 whip	+8 to +10	846	wolf, turtle, beaver
HLPM-3140A	3 Stage	3.5 v 8.5 ah Li	8.5x3.3x3.7	160-170	25	45-90	15	28 whip	+8 to +10	693	wolf, turtle, beaver
HLPM-3380	3 Stage	3.5 v 4.8 ah Li	8.5x3.3x2.5	130-140	25	55	15	28 whip	+8 to +10	475	fox, fawn, deer, bobcat
HLPM-3380A	3 Stage	3.5 v 4.8 ah Li	8.5x3.3x2.5	130-140	25	45-90	15	28 whip	+8 to +10	390	fox, fawn, deer, bobcat
HLPM-3124	3 Stage	3.5 v 3.2 ah Li	7.5x3.7x2.5	100-110	25	55	15	28 whip	+8 to +10	318	fox, fawn, deer, bobcat
HLPM-3124A	3 Stage	3.5 v 3.2 ah Li	7.5x3.7x2.5	100-110	25	45-90	15	28 whip	+8 to +10	260	fox, fawn, deer, bobcat
HLPM-3180	3 Stage	3.5 v 2.4 ah Li	8x2.2x2	55-65	20	50	11	28 whip	+3 to +5	435	bobcat, armadillo
HLPM-3180A	3 Stage	3.5 v 2.4 ah Li	8x2.2x2	55-65	20	45-90	11	28 whip	+3 to +5	328	bobcat, armadillo
HLPM-3150	3 Stage	3.5 v 1.6 ah Li	6.4x2.2x2	45-55	20	50	11	28 whip	+1 to +3	290	snowshoe hare, fawn
HLPM-3150A	3 Stage	3.5 v 1.6 ah Li	6.4x2.2x2	45-55	20	45-90	11	28 whip	+1 to +3	218	snowshoe hare, fawn
HLPM-3800	3 Stage	3.5 v 1.2 ah Li	5x2.1x1.5	28-36	20	50	11	28 whip	0 to +2	217	fox, woodchuck, marten
HLPM-3800A	3 Stage	3.5 v 1.2 ah Li	5x2.1x1.5	28-36	20	45-90	11	28 whip	0 to +2	163	fox, woodchuck, marten
LPM-3160	3 Stage	3.5 v 1600 ah LI	5x2.8x1.5	35-45	25	50	11	20 whip	-1 to +1	235	
LPM-3700	3 Stage	3.5 v 750 mah Li	3.5x2x1.5	18-30	20	50	10	22 whip	0 to -3	148	monkey, rabbit, ferret
LPM-3700A	3 Stage	3.5 v 750 mah Li	3.5x2x1.5	18-30	20	45-90	10	22 whip	0 to -3	112	monkey, rabbit, ferret
LPM-3350	3 Stage	3.5 v 350 mah Li	3x3x2.5	17-26	20	30	9	15 whip	-3 to -5	122	raccoon, beaver
LPM-3350A	3 Stage	3.5 v 350 mah Li	3x3x2.5	17-26	20	30-60	9	15 whip	-3 to -5	84	raccoon, beaver

Mounted weight may vary, depending on materials used.
Mortality can be added to these units and will affect days life and weight.
These are examples. Please contact us for you application.



Wildlife Materials, Inc.

1202 Walnut Street Murphysboro, Illinois 62966 USA
 USA 1-800-842-4537 FAX 1-618-687-3539 CANADA
 1-800-626-2704
www.wildlifematerials.com

Revised 9/2008